

Operating voltage _____ 85 to 250 V~
 Operating current _____ 4.0 Amp
 Operating frequency _____ 50/400 Hz
 Operating temperature, High _____ See temp. curves
 Operating temperature, Low _____ -55° C,
 Diel. withstanding (line - case) _____ 1500 Vac
 Diel. withstanding (line - line) _____ 1500 Vdc
 Leakage current _____ 2.0 ma @ 220 V, 60 Hz
 Max residual voltage after 1 sec. _____ 34 Volts
 The filter is available in both the standard model and the high temperature model.

The model Numbers are:
 Standard model: _____ HH-2178-4
 High temp model: _____ HH-2178-4HT

